



Total 1

INSTALLATION SITE PREPARATION CHECKLIST

General Machine Environment

- The installation area is clean and clear of dust and tools. It is not located in an active construction zone.
- The counter accommodates the machine size and weight:
 - Dimensions: 19.0" (W) x 44.0" (H) x 28.0" (D)
 - Dry weight: 145 lb
- For under counter waste bin installation, a hole is cut in the counter in accordance with the Emblem chute kit template.
- Machine can safely be installed with minimum clearance:
 - Top: 6" – Filling the coffee canisters from the top.
 - Sides: 6" – Opening the door and accessing the lock.
 - Back: 1.75" – Electrical and water connections space.

Electrical Requirements

The electrical configuration must match the Total 1 Site Preparation Checklist's electrical requirements, prior to request the installation of the coffee machine. To do so, **we recommend that you consult a qualified professional electrician.**

Model	120 V	240 V
Power Cord Plug	NEMA 5-20P	NEMA L14-20P
Max Absorbed Power	1440 W	3060 W
Voltage & Frequency	120 V / 60 Hz	220 V / 60 Hz

- Dedicated electrical circuit meets the Total 1 power requirements, according to the model.
- No extension cord or power strip on the circuit.

Water Specifications

The water configuration must match the Total 1 Site Preparation Checklist's water specifications, prior to request the installation of the coffee machine. To do so, **we recommend that you consult a water filtration system specialist.**

Pressure & Hardness

- Cold tap water pressure is at least 20 psi and no more than 80 psi.
- pH range is between 6 and 8.
- General hardness is between 10 and 70 mg/L.
- Machine water line is equipped with softness/filtration system and descaling device.

Water Network

- The water network provides cold, drinkable tap water.
- Dedicated 1/4" or 3/8" diameter water line.
- Easily accessible dedicated shutoff valve.

IMPORTANT: Do NOT use distilled water

