

INSTALLATION SITE PREPARATION CHECKLIST





GENERAL MACHINE ENVIRONMENT

- The counter accommodates the machine size and weight:
 - Dimensions: 17.7" (W) x 34.5" (H) x 20.7" (D)
 - Dry weight: 165 lb
- For under counter waste bin installation, a hole is cut in the counter in accordance with the 9100 chute kit template.
- Machine can safely be installed with minimum clearance:
 - Front: 20.7" Opening the door completely to fill the machine.
 - Sides: 2.2" Leaving a bit of room from the wall for correct ventilation.
 - Back: 4" Electrical and water connections space.

ELECTRICAL REQUIREMENTS

The electrical configuration must match the 9100 2C Site Preparation Checklist's electrical requirements, prior to request the installation of the coffee machine. To do so, we recommend that you consult a qualified professional electrician.

9100 2C Specifications	
------------------------	--

120 V / 60 HZ, 1260 W NEMA 5-15P GFCI

- Power outlet receptacle is NEMA 5-15R.
- Dedicated electrical circuit meets the 9100 power requirements.
- ☐ No extension cord or power strip on the circuit.





WATER SPECIFICATIONS

The water configuration must match the 9100 2C Site Preparation Checklist's water specifications, prior to request the installation of the coffee machine. To do so, we recommend that you consult a water filtration system specialist.

Pressure & Hardness

- Water pressure is between 11.6 psig and 123.2 psig (0.8 and 8.5 bar).
- pH range is between 6.5 and 7.5.
- ☐ Hardness (TDH) is between 89 PPM and 142 PPM.
- Machine water line is equipped with softness/filtration system and descaling device.

Water Network

- The water network provides cold, drinkable tap water.
- Dedicated 1/4" or 3/8" diameter water line.
- Easily accessible dedicated shutoff valve.





