

GENERAL MACHINE ENVIRONMENT

The installation area is clean and clear of dust and tools. It is not located in an active construction zone.

The counter accommodates the machine size and weight:

- Dimensions: 17.8" (W) x 30.5" (H) x 23.9" (D)
- Dry weight: Up to 94 lb

For under counter waste bin installation, a hole is cut in the counter in accordance with the Symbol chute kit template. Machine can safely be installed with minimum clearance:

- Top: 6" Filling the machine from the top.
- Sides: 6" Opening the door and access the lock.
- Back: 1.75" Electrical and water connections space.

ELECTRICAL REQUIREMENTS

The electrical configuration must match the Symbol Site Preparation Checklist's electrical requirements, prior to request the installation of the coffee machine. To do so, **we recommend that you consult a qualified professional electrician**.

Symbol Specifications	120 V / 60 HZ, 1440 W NEMA 5-15P GFCI
-----------------------	--

Power outlet receptacle is NEMA 5-15R.

Dedicated electrical circuit meets the Symbol power requirements.

No extension cord or power strip on the circuit.

WATER SPECIFICATIONS

The water configuration must match the Symbol Site Preparation Checklist's water specifications, prior to request the installation of the coffee machine. To do so, **we recommend that you consult a water filtration system specialist.**

Pressure & Hardness

- Cold tap water pressure is between 20 psi and 80 psi.
- pH range is between 6 and 8.
- General hardness is between 10 and 70 mg/L.
- Machine water line is equipped with softness/filtration system and descaling device.

Water Network

- The water network provides cold, drinkable tap water.
- Dedicated 1/4" or 3/8" diameter water line.
- Easily accessible dedicated shutoff valve.

IMPORTANT: Do NOT use distilled water



Evoca North America

2355, avenue Dalton, Québec (Québec) G1P 3S3, Canada T: 800-561-6162 - F: 800-463-2739 www.evocagroupna.com

Evoca Group Headquarters

Via Roma, 24, 24030 Valbrembo BG Italy T: +39 035606111 - F: +39 095606560 www.evocagroup.com

